



Conduzindo Alta Tecnologia

Tabela 1: Corrente consumida por potencia do alto-falante

Potência do canal	Impedância no condutor (ohms)			
	2 ohms	4 ohms	8 ohms	16 ohms
Watts RMS	Corrente (A)	Corrente (A)	Corrente (A)	Corrente (A)
20 / 40	5,0	3,0	2,0	1,5
40 / 60	6,0	4,0	3,0	2,0
60 / 80	7,0	5,0	3,0	2,0
80 / 100	7,0	5,0	3,5	2,5
100 / 120	8,0	6,0	4,0	3,0
120 / 140	8,0	6,0	4,0	3,0
140 / 160	9,0	6,0	4,5	3,0
160 / 180	9,5	7,0	5,0	3,0
180 / 200	10,0	7,0	5,0	3,5
200 / 220	11,0	8,0	5,0	4,0
220 / 240	11,0	8,0	5,0	4,0
240 / 260	11,5	8,0	6,0	4,0
260 / 280	12,0	8,5	6,0	4,0
280 / 300	12,0	9,0	6,0	4,0
300 / 400	14,0	10,0	7,0	5,0
400 / 500	16,0	11,0	8,0	5,5
500 / 600	18,0	12,0	9,0	6,0

Tabela 2

Cabos para Alto-falantes	
Corrente no condutor (A)	Seção dos cabos (mm ²)
1,0 - 1,5	0,50
2,0 - 2,5	0,75
3,0	1,00
3,5 - 4,0	1,30
4,5 - 5,0	1,50
6,0 - 7,0	2,00
8,0	2,50
9,0	3,00
10,0 - 11,0	3,50
12,0 - 13,0	4,00
14,0 - 15,0	5,00
16,0 - 17,0	6,00

Entre em contato com a Discabos

www.discabos.com.br

sac@discabos.com.br